GENERATOR SET MODEL (EM-150)

GENERATOR SET MODEL (HM-150)

Technical Data Sheet





| GENERATOR SET MODEL (EM-130) | | | | | | | |
|-----------------------------------|----------------------------------|------------------------------------|---------------------------------|--|--|--|--|
| OUTPUT | T RATINGS | PRIME | STANDBY | | | | |
| 240-415 V, 3 ph | ı, 50 Hz, <mark>150</mark> 0 rpm | 150 KVA (120 KW) | 165 KV <mark>A (</mark> 132 KW) | | | | |
| ENGINE / TECH | NICAL DATA | | | | | | |
| Engine Make | | Perkins | | | | | |
| Engine Model | | 1106C-70TAG2 | | | | | |
| Governing Type | | Mechanical | | | | | |
| Number of Cylind | ders | 6 | | | | | |
| Cylinder Arrange | ment | Vertical in line | | | | | |
| Bore and Stroke | | 105 mm x 135 mm | | | | | |
| Displacement / 0 | Cubic Capacity | 7.01 L | | | | | |
| Induction System | ١ | Turbocharged | | | | | |
| Cycle | | 4 stroke | | | | | |
| Combustion System Indi | | | Injection | | | | |
| Compression Rat | tio | 18.2 : 1 L | | | | | |
| Rotation | | Anti-clockwise, viewed on flywheel | | | | | |
| Cooling System | | Water - cooled | | | | | |
| Frequency and Engine Speed | | 50 Hz & 1500 rpm | | | | | |
| | | PRIME | STANDBY | | | | |
| Gross Engine Pov | ver | 136 kW (182.3 hp) | 149.1 kW (200 hp) | | | | |
| Fuel Consumption | n @ 50% load | 16.4 L/hr | - | | | | |
| | @ 75% load | 24.7 L/hr | | | | | |
| | @ 100% load | 33.4 L/hr | 36.1 L/hr. | | | | |
| Total Lubrication System Capacity | | 16.5 L | 16.5 L | | | | |
| Total Coolant Cap | pacity (Inc. radiator) | 21 L | 21.0 L | | | | |
| Exhaust Tempero | ature | 484°C | 484°C | | | | |
| Radiator Cooling | a Air Flow (Min) | $4.7 \text{ m}^3/\text{s}$ | $4.7 \text{ m}^3/\text{s}$ | | | | |
| Combustion Air F | low | 10.2 m ³ /min | 10.76 m ³ /min | | | | |
| F. d | | 27.70 3 /: | OF F7 7/ · | | | | |

| ALTERNATOR DATA | | | | |
|-----------------------------|-----------------|--|--|--|
| Make | Leroy Somer | | | |
| Model | TAL 044J | | | |
| No. of bearings | 1 | | | |
| Insulation class | Н | | | |
| Total Harmonic Content | Not on load <3% | | | |
| Wires | 6 | | | |
| Ingress Protection | IP23 | | | |
| Excitation System | SHUNT | | | |
| Winding Pitch | 2/3 (n°3) | | | |
| AVR Model | R120 | | | |
| Overspeed | 2250 mn-1 | | | |
| Voltage Regulation (steady) | ±1% | | | |
| Short Circuit Capacity | - | | | |
| | | | | |

GENERAL SPECIFICATIONS

1. ENGINE

Perkins four stroke heavy duty high performance industrial type diesel engine.

2. COOLING RADIATOR

Radiator and cooling fan, complete with safety guards, designed to cool the engine at high ambient temperatures. (Consult your dealer for deration factors)

3. EXHAUST SYSTEM

Heavy duty Industrial Exhaust Silence.

| Silencer noise reduction level | 12 (dB) |
|---------------------------------|-----------|
| Maximum allowable back pressure | 6.0 (kPa) |

4. CIRCUIT BREAKER TYPE

ABB 3 pole MCCB. (4 pole is optional)

5. FUEL SYSTEM

The base frame design can be incorporated with an integral fuel tank with a capacity of approx. 8 hours running at Full Load. The tank is supplied complete with fill cap breather, fuel feed and return lines to the Engine and drain plug.

6. ALTERNATOR

INSULATION SYSTEM

- The insulation system is Class H.
- · All windings are impregnated in either a triple dip thermosetting liquid, oil and acid resisting polyester varnish or vacuum pressure impregnated with a special polyester resin.
- Heavy coat of antitracking varnish additional protection against moisture or condensation.

AUTOMATIC VOLTAGE REGULATOR

The fully sealed Automatic Voltage Regulator maintains the Voltage Regulation at ±1%. Nominal adjustment by means of a trim pot incorpoated on the AVR.

(cont.)

25.53 m³/min

259 L

Exhaust Gas Flow

Fuel Tank Capacity

23.78 m³/min

259 L

GENERATOR SET MODEL (HM-150)

Technical Data Sheet



CONTROL PANEL

Make **DEEP SEA** Model **DSE6120**

The **DSE6120** is an Auto Start Control Module for single genset applications. It includes a backlit LCD display which clearly shows the status of the engine all the times. This module can either be programmed using the front panel or by using the DSE configuration suite PC software.

METERING AND ALARM INDICATIONS:

- Generator frequency
- Underspeed, Overspeed
- Generator volts (L-L, L-N)
- Generator current
- · Loss of magnetic pick-up signal Optional
- Fuel level (Warning or shutdown) Optional
- Failed to reach loading voltage/frequency
- CAN diagnostics and CAN fail/error

- Engine oil pressure
- Engine coolant temperature
- Battery volts
- Fail to start/stop
- Emergency stop
- Charge fail
- Low DC voltage
- Hours run counter

| DIMENSIONS AND WEIGHT | | | | | | | |
|-----------------------|------------------------|---------|---------|---------|--|--|--|
| | Length | Width | Height | Weight | | | |
| Closed Type | 3200 mm | 1100 mm | 1800 mm | 2180 kg | | | |
| Open Type | 235 <mark>0 m</mark> m | 950 mm | 1520 mm | 1580 kg | | | |

RATINGS DEFINITION

Prime Power

These ratings are applicable for supplying continuous electrical power (at variable load) in lieu of commercially purchased power.

10% overload power is available for 1 hour in 12 hours continuous operation.

Standby Power

These ratings are applicable for supplying continuous electrical power (at variable load) in the event of a utility power failure. No overload is permitted on these ratings.

STANDARD REFERENCE CONDITIONS

Output ratings are presented at 25°C air inlet temperature, barometric pressure 100 kPa, relative humidity 30%. This generating set is designed to operate at high ambient temperatures (up to 55°C), humidity (up to 99%) and higher altitudes. Deration may apply, please consult your dealer for specific site ratings.

AVAILABLE OPTIONS & ACCESSORIES

We offer a range of optional features and accessories to tailor our generatin sets to meet your power needs.

OPTIONS

- A variety of generating set control and synchronizing panels
- · Additional protection alarms and shutdowns
- Water fuel separator
- Water jacket heater
- Battery charger

ACCESSORIES

- Genuine spare parts
- · Load banks
- Auxiliary fuel tanks
- Manual & automatic transfer switches

GENERAL SPECIFICATIONS

MOTOR STARTING

An overload capacity equivalent to 300% of the Full Load impedance at zero Power Factor can be sustained for 10 seconds, when PMG option is fitted.

7. MOUNTING ARRANGEMENT

BASE FRAME

The complete Generating Set is mounted as a whole on a heavy duty fabricated steel Base frame.

· COUPLING

The Engine and Alternator are directly coupled by means of an SAE flange.

The Engine flywheel is flexibly coupled to the Alternator rotor.

ANTI-VIBRATION MOUNTING PADS

Anti-Vibration pads are affixed between the Engine/Alternator feet and the Base frame thus ensuring complete vibration isolation of the rotating assembly.

SAFETY GUARDS

The Fan & Fan Drive along with the Battery Charging Alternator are Safety Guard protected for personnel protection.

8. FACTORY TESTS

- The Generating set is load tested before dispatch
- All protective devices control functions and site load conditions are simulated.
 The generator and it's systems are checked before dispatch.

9. EQUIPMENT FINISHING

All mild steel components are fully degreased and painted with powder coated paint to ensure maximum scuff resistance and durability.

10. DOCUMENTATIONS

The base frame design can be incorporated with an integral fuel tank with a capacity of approx. 8 hours running at Full Load. The tank is supplied complete with fill cap breather, fuel feed and return lines to the Engine and drain plug.

11. QUALITY STANDARDS

The equipment meets the following standards: BS4999, BS5000, BS5514 IEC 60034, VDE0530, NEMA MG 1.22 and ISO 8528.

12. WARRANTY

All of the Generating Sets provided by Hulool Motors are covered under a warranty policy for a period of 12 months.